



put 104 CD cap for all ICs from positive to negative close to IC, even if omitted in circuit, for opamps on dual supply two caps.
unused inputs of logic and opamps pull up or down to avoid oscillations and noise. connect supply of all chips if not mentioned.
"analog ground" and "digital ground" must be linked at power supply only, avoid loops, let grounds radiate from a ground plane.
use MFR 1% for all Resistors, 33E means 33 ohms, 22K means 22 kilo ohms, 1M is 1 megohm. 10T tp means ten turn trimpot.
'474 CD' is 47 with 4 zeros pF, 470000 pF, 470 nF, 0.47uF. "pl" is plastic, low leakage multilayer.

delabs

<http://delabs.topcities.com/>
<http://delabs.netfirms.com/>
<http://delabs.tripod.com/>
<http://geocities.com/delabs/>
<http://members.fortunecity.com/delabs/>

Use Terminal Block for Battery if you want to mount it outside the PCB.

delabs circuits and technologies

Title	
Size	Document Number
B	del90005
Rev 2	

Date: Monday, December 20, 2004 Sheet 1 of 1